

# Alfa

## ASIAN FUSION PENDANTS

### HARMONY

### P156

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

#### PRODUCT DESCRIPTION

The hand-blown, iridescent swirled P156 glass is fitted with a decorative finial cap and cordset in Vintage Bronze finish.  
12V 50W max. JC Lamp included.

Pendant Kit includes: Quick Jack Cord Set - 78" Coaxial Cable  
• Cordset can be shortened in the field • Glass Shade & Lamp Cover • 12V 50W JC Lamp



#### ORDERING INFORMATION

Model	Mounting Adapter	Hardware Finish	Example
<b>P156</b>	<b>QJ</b> QJ Pendant with Quick Jack Adapter* MP Pendant on Single Dome MonoPoint MC Pendant on Single Cone MonoPoint MB3 3X Pendants on Arched Bar MP3 3X Pendants on Large Dome	<b>BRZ</b> BRZ Vintage Bronze	<b>P156QJ-BRZ-HAR</b>

\*For use on Alfa Quick Jack Systems

#### PRODUCT SPECIFICATIONS

##### Electrical

**Lamp:** 12V 50W max. JC Lamp included, GY6.35

**Socket:** Ceramic Bi-Pin Socket, accepts G4 and GY6.35 Lamps

##### Agency Approval

**Labels:** ETL classified to UL 1598 for use in U.S. • ETL classified to CSA C22.2 No. 250 for use in Canada.

##### Mounting Specifications

**QJ:** Supplied with Quick Jack Adapter for use on MonoTrack.


**MP:** Supplied on a Non-Quick Jack (905 type) Slim Line MonoPoint. Internal 60W Electronic Transformer. Dimmable\*.

**MC:** Supplied on a Non-Quick Jack (908 type) Cone MonoPoint. Internal 60W Magnetic Transformer. Dimmable\*.

**MB3:** 3X Pendants supplied on a Non-Quick Jack (99003 type) Triple Arched Bar MonoPoint. Internal 150W Electronic Transformer. Dimmable\*.

**MP3:** 3X Pendants supplied on a Non-Quick Jack (99014 type) Triple Large Dome MonoPoint. Internal 200W Magnetic Transformer. Dimmable\*.

#### DIMENSIONS



\*Alfa recommends the use of Solid State (Electronic) Dimmers with Alfa products with Electronic Transformers. Magnetic Transformers may be dimmed with a quality Incandescent Dimmer.